



GE CONCORD 4 HOME SECURITY SYSTEM

FUNCTION	BUTTONS TO PRESS	RESULT
ARM PERIMETER DOORS/WINDOWS ONLY (STAY)	PRESS 2 OR STAY <i>(press 5 key before arming for SILENT ARMING)</i>	DISPLAY SHOWS "ARMED TO STAY" SYSTEM KEYPAD COUNTS DOWN DURING EXIT TIME
ARM PERIMETER WITH NO DELAY (INSTANT STAY)	PRESS 2 OR STAY 3 OR AWAY then PRESS 4 (NO DELAY) ARMS SYSTEM INSTANTLY	SYSTEM ARMS WITH EXIT DELAY, BUT DISABLES ENTRY DELAY DURING THIS ARMING CYCLE
ARM ENTIRE SYSTEM WITH PERIMETER DOORS/WINDOWS AND MOTION SENSORS (AWAY)	PRESS 3 OR AWAY	DISPLAY SHOWS "ARMED TO AWAY" SYSTEM KEYPAD COUNTS DOWN DURING EXIT TIME
DISARM SYSTEM	PRESS 1 (OFF) OR DISARM ENTER USER CODE	DISPLAY SHOWS DATE & TIME OR PROGRAMMED TEXT
BYPASS ZONE(S)	ARM SYSTEM TO DESIRED LEVEL THEN PRESS # (BYPASS) with zones open you wish to bypass.	LEAVE DESIRED DOORS/WINDOWS OPEN 2 or "STAY" Mode 3 or "AWAY" Mode "PROTEST" WILL DISPLAY ON KEYPAD PRESS "#" TO AUTOMATICALLY BYPASS OPEN ZONES
SEND A POLICE, FIRE OR AUXILIARY 24 HOUR ALARM ACTIVATION	1) PRESS AND HOLD POLICE BADGE FOR TWO SECONDS 2) PRESS AND HOLD FIRE SYMBOL FOR TWO SECONDS 3) PRESS AND HOLD RED CROSS FOR TWO SECONDS	1) POLICE ALARM WILL BE SENT TO CENTRAL MONITORING STATION 2) FIRE ALARM WILL BE SENT TO CENTRAL MONITORING STATION 3) AUXILIARY ALARM WILL BE SENT TO CENTRAL MONITORING STATION
TURN CHIME ON/OFF	PRESS 7 (FEATURES) PRESS 1 (OFF)	CHIME WILL TURN ON OR OFF
CANCEL/SILENCE ALARM SILENCE TROUBLE BEEPS	PRESS 1 (OFF) ENTER USER CODE PRESS * KEY THEN DISARM SEQUENCE (1 plus User Code).	DISPLAY SHOWS ZONE(S) THAT TRIGGERED SIREN IS SILENCED ALARM IS CANCELLED SYSTEM WILL DISPLAY CURRENT OR PAST TROUBLE CONDITION, THEN SILENCE THE BEEPING.
RESET SMOKE DETECTORS	PRESS 1 (OFF) ENTER USER CODE REPEAT AFTER SMOKE CLEARS	DISPLAY SHOWS ZONE(S) THAT TRIGGERED SIREN IS SILENCED ALARM IS CANCELLED

PENINSULA SECURITY SYSTEMS INC.

590 West 9th Street - San Pedro, CA 90731

PHONE: (310)514-3144 - FAX (310) 832-6769- EMAIL: pensecursu@yahoo.com

www.peninsulasecurity.net