



QUICK REFERENCE GUIDE: GE NX8 ALARM PANEL

FUNCTION	BUTTONS TO PRESS	RESULT
ARM PERIMETER (STAY)	*PRESS STAY	*DISPLAY WILL READ "SYSTEM ARMED" * ARMED AND STAY LIGHTS WILL BE LIT
ARM PERIMETER WITH NO DELAY (INSTANT STAY)	*PRESS STAY	* NO ENTRY DELAY ON DOORS
ARM ENTIRE SYSTEM (AWAY)	*PRESS EXIT	*DISPLAY WILL READ "SYSTEM ARMED" * EXIT LIGHT WILL BE ON
DISARM SYSTEM/CANCEL AN ALARM	*ENTER USER CODE	*DISPLAY WILL READY "SYSTEM READY" * ARMED LIGHT WILL TURN OFF
BYPASS ZONE(S)	1) PRESS * SCROLL TO FIND THE ZONE(S) YOU WANT BYPASSED 2) PRESS BYPASS WHILE ZONE IS DISPLAYED 3) PRESS BYPASS TWICE TO EXIT THIS FUNCTION	1) ZONE DESCRIPTIONS WILL BE DISPLAYED 2) BYPASS LIGHT WILL FLASH 3) BYPASS LIGHT WILL STOP FLASHING
TURN CHIME ON/OFF	*PRESS CHIME	* CHIME LIGHT WILL TURN ON OR OFF
TESTING THE SYSTEM	*PRESS * *ENTER USER CODE TO SILENCE THE SIREN	*THE SYSTEM WILL TEST THE SIREN, BATTERY AND COMMUNICATOR
SEND AN EMERGENCY, MEDICAL OR FIRE ALARM ACTIVATION	*PRESS AND HOLD THE APPROPRIATE BUTTON FOR TWO SECONDS 	*SIREN WILL SOUND *EMERGENCY, MEDICAL, OR FIRE ALARM SIGNAL WILL BE SENT TO PENINSULA SECURITY MONITORING CENTER
RESET SMOKE DETECTORS, ZONE TROUBLES AND ZONE TAMPERS	*DISARM THE SYSTEM IF ARMED *PRESS *	*SMOKE DETECTORS, TAMPERS AND TROUBLES WILL RESET
CHANGE YOUR USER CODE	*PRESS * * ENTER USER CODE *ENTER 3-DIGIT USER NUMBER (I.E. "003" FOR USER 3) *TYPE IN NEW CODE *TO EXIT FUNCTION PRESS *	* NEW USER CODE WILL TAKE AFFECT

PENINSULA SECURITY SYSTEMS INC.

590 West 9th Street - San Pedro, CA 90731

PHONE: (310)514-3144 - FAX (310) 832-6769- EMAIL: pensecursu@yahoo.com